Ammyy V3 遠端遙控軟體[被控端]-操作文件

[步驟 1] 點選 Ammyy V3 程式後,若出現下面畫面請點選[執行]



[步骤 2] 點選 [Start] 告訴要遙控你電腦的人 Your ID 框框內的數字,如下圖:

PS:若 Start 已經反白,就不需要點選了,直接告訴要遙控你電腦的人 Your ID 框框内的數字

Ammyy Admin v3.0 - Free	
Ammyy Language Help	Free license (for home use only!)
Client. Wait for session 告訴要遙控你電腦的人這個ID	Operator. Create session
Your ID 5 992 733	Client ID/ IP
Your IP 192.168.2.102	Desktop - speed 256 Kb - 1 Mb View only
1. Start Stop	Connect
Connected to router '50.115.127.37:443' successfully	

[步驟 3] 當遠端遙控的人要連到你電腦時,會出現如下的視窗,請按下[Accept]按鈕,如下圖: (每次遠端遙控的人要連到你的電腦時,都會出現這個視窗)

Ammyy Admin
Operator [ID= 456] is connecting to your PC.
View screen
Remote control
V File manager
✓ Audio chat
☑ RDP sessions
Acception Reject

當你不需要被遠端電腦遙控時,請點選遙控軟體視窗右上角的[X],即可切斷遠端遙控,如下圖:

Ammyy Admin v3.0 - Free	
Ammyy Language Help	Free license (for home use only!)
Client. Wait for session	Operator. Create session
Your ID 5 992 733 Your IP 192.168.2.102	Client ID/ IP Desktop - speed 256 Kb - 1 Mb View only
Start Stop Connected to router '50.115.127.37:443' successfully	Connect

※ 若你不希望每次遙控端要連線到你的電腦時,你都必須做[步驟 3]的動作遙控端才可以連線,請依 照下列步驟設定一次即可(永久有效):

myy Language Help	Free license (for home use only!
Settings sessi	on Operator. Create session
Service	Client ID/ IP
Exit	
Your IP	Desktop - speed <256 Kb
5 192.168.2.102	View only
Start	top Connect

[步驟 A] 請依照下列畫面點選。

[步驟 B] 請依照下列畫面點選。

Ammyy - Settings	X
Client Operator Common Network	
 Start "wait for session" mode automatically Show tooltip - mouse cursor blinking cause Disable desktop background Disable visual effects Disable desktop composition 	
2. Access Permissions	
Video system speed test	
	確定 取消

[步驟 C] 請依照下列畫面點選。

computer ID	Password	Screen	Files	Permissions
				View screen
				Remote control
				Copy clipboard of client
				Copy clipboard of operator
				File manager
				Voice chat
				RDP connection
	12-			
Add	Edit] [R	emove	

[步驟 D] 請依照下列畫面點選。

computer ID Password Screen Files Permissions	
Ammyy - Access Permissions	
Computer ID: ANY <-自動產生的不需輸入 pboard of client	
Leave password empty if no password authentication required pboard of opera	ator
Password:	
ction	
OK Cancel	
Add Edit Remove	
Protect these settings from remote operator OK	

[步驟 E] 請依照下列畫面點選。

computer ID	Password	Screen	Files	Permissions	
	Ammyy	- Access P	ermissions		
		Computer ID:	ANY	control	
ſ	Ammyy Ad	min		X	of client
	Do y	you want to conti	inue?		
				(1) 否 (1) 是	
A 1.1			omouo		

[步驟 F] 設定完成的資料如下圖,紅色字體為說明。

Ammyy - Access Permissions	X
computer ID Password Screen Files	Permissions
ANY 設定完成的資料如上. 說明: ANY的意思是說你當你開啟遠端遙控軟體 時,遙控端可以直接連到你的電腦,你不需要 每次都按[Accept]同意後,他才可以連線.	 View screen Remote control Copy clipboard of client Copy clipboard of operator File manager Voice chat RDP connection
Add Edit Remove	ОК
	確定取消

[步驟 G] 請依照下列畫面點選。

Ammyy - Settings	
Client Operator Common Network Image: Start "wait for session" mode automatically Image: Start "wait for session" mode automatically Image: Start "wait for session" mode automatically Image: Start "wait for session" mode automatically Image: Start "wait for session" mode automatically Image: Start "wait for session" mode automatically Image: Start "wait for session" mode automatically Image: Start "wait for session" mode automatically Image: Start Transition of the start star	
Access Permissions	
	確定取消

※以上就完成了被控端不需要每次連線時都要按[Accept],遙控端才可以連入的設定了。