

Console Reset Nusoft MH-700 and MS-700

1. Use console cable connects the console port of MH-700 or MS700 to PC com port
2. Open HyperTerminal



3. Create a new connection and select com port setting



4. Press "Enter" button to enter console mode
5. The username and password are both "itsecurity"
6. Enter "reset" command
7. Firewall will be restored to factory default after 10 min
8. Login <http://192.168.1.1> with username and password are both "admin".